HANBELL

RC2-180A Screw Compressor-R134a

Specifications		Displacement	CFM	60 Hz	127	
speerrieacions		Rated Speed	Rpm	60 Hz	3550	
		Nominal Hp			42 at 60Hz	
	Compressor	Volume Ratio	Vi		2.6 (standard other Vi available)	
		Capacity Control	%		33%,66% & 100% Step Capacity Control, 33%~100% Continuous Stepless Capacity Controls	
		Lubrication			Differential Pressure Feed Lubricant	
		Туре			3 Phase, 2 Pole, Squirrel Cage, Induction Motor	
	Motor	Insulation			Class F	
		Protection			3 PTC Protection 1 per winding	
	Lubricant Charge	Gallons			1.9	
	Oil Heater	Watts			150	
	Hydrostatic Pressure test	lb/in ² G			597	
	Weight	Pounds			661	

Standard Compressors Accessories

Modulating Slide Capacity

ICRO


ONTROL YSTEMS

- Weather Proof Terminal Box for outdoor •
- applications
- . 115/1/60 Control Voltage
- 115/1/60 Crankcase heater .
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings
- Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings

- Oil Level Float Switch
- Suction Filter
- Oil Filter
- PSI Relief Valve
- **Oil Sight Glass**
- PT1000 for Reading Motor Temp
- INT69HBY supporting motor and . discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

Ports

- External Oil Cooler
- Liquid Injection (into screw chamber)
- Economizer
- Suction, Discharge & Oil Service



Connections **Discharge Stop Valve** 1 1/2" **Horizonal Discharge** 1 1/2" **Check Valve Suction Stop Valve** 2 1/2" 5/8" solder Economizer Liquid Injection (chamber) 5/8" flare **Discharge Side** Copper Pipe Sizing 1 5/8" **Suction Side** Copper Pipe Sizing 2 5/8" 2.36" 4.33" 1.38" 2.63" 3.03"

MCC & LRA

Optimized for R134a

	Volts	Maximum Continuous Current	Y	-Δ	Part Wind Start	
Hertz			Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)
60	220	202	198	595	305	610
60	460	96	108	325	163	325