



APPLICATION NOTE

APP126

Revision History

Date	Author	Description
03-30-17	DEW	Setup

Setting the Graphics Lock Feature for MCS-Connect on MCS-TOUCH

Any questions regarding this release, contact: support@mcscontrols.com


Micro Control Systems, Inc. 5580 Enterprise Parkway Fort Myers, Florida 33905
(239)694-0089 FAX: (239)694-0031 www.mcscontrols.com

Information contained in this document has been prepared by Micro Control Systems, Inc. and is copyright © protected 2017.
Copying or distributing this document is prohibited unless expressly approved by MCS.



This app note will explain how to lock the touchscreen into the graphics screen so unauthorized users can't get to the Status screen.

Start by Unlocking the Touchscreen.

1. Click on the 'MCS TOOLS' folder on the desktop, 'MEMORY LOCK' sub folder will appear when this file is opened..




2. Double click on the 'Memory lock' folder
3. Double click on the 'Unlock Memory' icon




4. Next screen, click on 'Execute'
5. Touchscreen will perform a restart
6. Check on desktop screen to make sure the touchscreen shows 'UNLOCKED'



1. Click on the 'MCS TOOLS' on desktop once Touchscreen restarts.



2. Click 'Magnum Hex' on bookmark bar.




3. Click 'Go' on top menu bar,' then select 'Parent Folder'

4. Right click mcspc2.ini



5. Click 'Leafpad' to edit the file.



6. Change Graphics parameter to 1.



7. Save mcspc2.ini file.




NEXT STEP - RE LOCK TOUCHSCREEN - SEE NEXT PAGE

Locking MCS-TOUCH

Re-Locking Touchscreen (follow the 4 steps below)



1. Double click the 'MCS TOOLS' Icon on the Desktop.
2. Double click 'Memory Lock' sub directory.
3. Double click 'Lock Memory'.
4. Click 'EXECUTE'. The touchscreen will reboot.



Click to LOCK touchscreen
Click to Execute

