## RC2-200A Screw Compressor-R134a

Displacement	CFM	60 Hz	137		
Rated Speed	Rpm	60 Hz	3550		
Volume Ratio	Vi		2.6 (standard other Vi available)		
Nominal Hp			45 Hp at 60 Hz		
Capacity Control	%		25%,50%,75% & 100% Step Capacity Control, 50%~100% Continuous Stepless Capacity Controls		
Lubrication			Differential Pressure Feed Lubricant		
Туре			3 Phase, 2 Pole, Squirrel Cage, Induction Motor		
Insulation			Class F		
Protection			3 PTC Protection 1 per winding		
			No internal oil separator or sump		
lb/in <sup>2</sup> G			597		
Pounds			926		
	Rated Speed     Volume Ratio     Nominal Hp     Capacity Control     Lubrication     Type     Insulation     Protection     Ib/in <sup>2</sup> G	Rated Speed Rpm   Volume Ratio V   Nominal Hp V   Capacity Control 9   Lubrication 9   Insulation   Protection   lb/in <sup>2</sup> G	Rated SpeedRpm60 HzVolume RatioViNominal Hp%Capacity Control%Lubrication%TypeInsulationProtection1b/in²G		

## Standard Compressors Accessories

HANBELL

Modulating Slide Capacity

ICRO ONTROL SYSTEMS

Spe

- Weather Proof Terminal Box for outdoor applications
- 115/1/60 Control Voltage
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings
- Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings

**Discharge Stop Valve** 

**Horizonal Discharge** 

**Suction Stop Valve** 

**Check Valve** 

Economizer

Suction Filter

Connections

## PSI Relief Valve

- Oil Sight Glass
- PT1000 for Reading Motor Temp

2"

2"


2 1/2"

5/8" solder

 INT69HBY supporting motor and discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

## Ports

- External Oil Cooler
- Liquid Injection (into screw chamber)
- Economizer



Liquid Injection (chamber)	5/8" flare	A	В	С	D	E
Discharge Side	Copper Pipe Sizing 2 1/8"	1.99"	3.54"	1.18"	2.14"	2.56"
Suction Side	Copper Pipe Sizing 2 5/8"	2.36"	4.33"	1.38"	2.63"	3.03"

MCC &	LRA	Optimizer for R134a							
	Hertz Volt		Maximum Continuous Current	Y	-Δ	Part Wind Start			
		Volts		Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)		
	60	220	214	198	595	305	610		
	60	460	102	108	325	163	325		