HANBELL

RC2-260A Screw Compressor-R134a

cations	Displacement	CFM	60 Hz	182	
	Rated Speed	Rpm	60 Hz	3550	
	Volume Ratio		ï	2.6 (standard other Vi available)	
Compressor	Nominal Hp			90 Hp at 60 Hz	
	Capacity Control	%		25%,50%,75% & 100% Step Capacity Control 50%~100% Continuous Stepless Capacity Contro	
	Lubrication			Differential Pressure Feed Lubricant	
	Туре			3 Phase, 2 Pole, Squirrel Cage, Induction Motor	
Motor	Insulation	n		Class F	
	Protection			3 PTC Protection 1 per winding	
Lubricant Charge	Gallons			3.7	
Oil Heater	Watts			150	
Hydrostatic Pressure test	lb/in ² G			597	
Weight	Pounds			1235	

Standard Compressors Accessories

Modulating Slide Capacity

ICRO

Specif

ONTROL YSTEMS

- Weather Proof Terminal Box for outdoor applications
- 115/1/60 Control Voltage
- 115/1/60 Crankcase heater
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings

Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings

- Oil Level Float Switch
- Suction Filter
- **Oil Filter**

•


- **PSI Relief Valve**
- Oil Sight Glass
- PT1000 for Reading Motor Temp

2"

INT69HBY supporting motor and discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

Ports

- External Oil Cooler
- Liquid Injection (into screw chamber)
- Economizer
- Suction, Discharge & Oil Service



Horizonal Discharge	onnections	Discharge Stop Valve
Check valve		Horizonal Discharge Check Valve

2"			- H	1 <u> </u>	
3"					
5/8" solder					
5/8" flare		В	С	D	Е
Copper Pipe Sizing 2 1/8"	1.97"	3.54"	1.18"	2.14"	2.56"
Copper Pipe Sizing 3 1/8"	2.60"	4.72"	1.77"	3.14"	3.54"
	3" 5/8" solder 5/8" flare Copper Pipe Sizing 2 1/8"	2 3" 3" 5/8" solder 5/8" flare A Copper Pipe Sizing 2 1/8" 1.97"	2 3" 3" 5/8" solder 5/8" flare A Copper Pipe Sizing 2 1/8" 1.97"	3"	3"

MCC & LRA

Optimizer for R134a

		Maximum	Y	-Δ	Part Wind Start		
Hertz	Volts	Continuous Current	Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)	
60	220	286	302	905	618	1030	
60	460	137	167	500	285	475	