5580 Enterprise Parkway, Fort Myers, FL 33905 Office: 239-694-0089 Fax: 239-694-0031 www.mcscontrols.com

RC2-410A Screw Compressor- R134a

ications	Displacement	CFM 60 Hz		288		
	Rated Speed	Rpm 60 Hz		3550		
	Volume Ratio	Vi		2.6 (standard other Vi available)		
Compressor	Nominal Hp			93 Hp at 60 Hz		
	Capacity Control	%		25%,50%,75% & 100% Step Capacity Control, 50%~100% Continuous Stepless Capacity Controls		
	Lubrication			Differential Pressure Feed Lubricant		
	Туре			3 Phase, 2 Pole, Squirrel Cage, Induction Motor		
Motor	Insulation	on		Class F		
	Protection			3 PTC Protection 1 per winding		
Lubricant Charge	Gallons	-		4.0		
Oil Heater	Watts			300		
Hydrostatic Pressure te	est lb/in ² G			597		
Weight	Pounds			1609		

Standard Compressors Accessories

HASBELL

Modulating Slide Capacity


CRO ONTROL YSTEMS

Specif

- Weather Proof Terminal Box for outdoor applications
- 115/1/60 Control Voltage
- 115/1/60 Crankcase heater
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings
- Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings
- Oil Level Float Switch
- Suction Filter
- Oil Filter .
- **PSI Relief Valve** .
- Oil Sight Glass
- PT1000 for Reading Motor Temp
- INT69HBY supporting motor and • discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

Ports

- External Oil Cooler
- Liquid Injection (into screw chamber)
- Economizer
- Suction, Discharge & Oil Service



Connections	Discharge Stop Valve
-------------	----------------------

Discharge Stop Valve	2 1/2"	2 1/2"				7	
Horizonal Discharge Check Valve	2 1/2"].	
Suction Stop Valve	4"			-	Å		
Economizer	7/8" solder						
Liquid Injection (chamber)	5/8" flare	Α	В	С	D	Е	
Discharge Side	Copper Pipe Sizing 2 5/8"	2.36"	4.33"	1.38"	2.63"	3.03"	
Suction Side	Copper Pipe Sizing 4 1/8"	2.99"	5.71"	1.97"	4.14"	4.57"	

MCC	MCC & LRA Optimized for R134a							
		Volts	Maximum Continuous Current	Υ-Δ		Part Wind Start		
	Hertz			Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)	
	60	460	215	243	730	497	765	