

Specifi



## RC2-580A Screw Compressor-R134a

ications		Displacement	CFM 60 Hz		413		
	cacions	Rated Speed	Rpm 60 Hz		3550		
		Volume Ratio	Vi		2.6 (standard other Vi available)		
	Compressor	Nominal Hp			131 Hp at 60 Hz		
		Capacity Control	%		35%,50%,75% & 100% Step Capacity Control, 50%~100% Continuous Stepless Capacity Controls		
		Lubrication			Differential Pressure Feed Lubricant		
		Type	on		3 Phase, 2 Pole, Squirrel Cage, Induction Motor		
	Motor	Insulation			Class F		
		Protection			3 PTC Protection 1 per winding		
	Lubricant Charge	Gallons	Ī		5.3		
	Oil Heater	Watts			300		
	Hydrostatic Pressure test	lb/in <sup>2</sup> G			597		
	Weight	Pounds			1775		


## **Standard Compressors Accessories**

- Modulating Slide Capacity
- Weather Proof Terminal Box for outdoor applications
- 115/1/60 Control Voltage
- 115/1/60 Crankcase heater
- Horizonal Discharge Check Valve
- Discharge Service Valve (Discharge Stop Valve) with standard connection sizes and supplied with flanges and bushings
- Suction Service Valve (Suction Stop Valves) with standard connection sizes and supplied with flanges and bushings

- Oil Level Float Switch
- Suction Filter
- Oil Filter
- PSI Relief Valve
- Oil Sight Glass
- PT1000 for Reading Motor Temp
- INT69HBY supporting motor and discharge (PTC) temperature sensor protection as well as Phase Loss and Phase Reversal at Start Up Only

## **Ports**

- External Oil Cooler
- Liquid Injection (into screw chamber)
- **Economizer**
- Suction, Discharge & Oil Service



## Connections

5	Discharge Stop Valve	3"		
	Horizonal Discharge Check Valve	3"		
	Suction Stop Valve	4"		
	Economizer	1 1/8" solder		
	Liquid Injection (chamber)	5/8" flare	Α	
	Discharge Side	Copper Pipe Sizing 3 1/8"	2.59"	ĺ
Г	Suction Side	Copper Pipe Sizing 4 1/8"	2.99"	ĺ

Α	В	С	D	Ε
2.59"	4.72"	1.77"	3.14"	3.54"
2.99"	5.71"	1.97"	4.14"	4.56"

MCC & LRA Optimized for R134a							
			Maximum	Υ-Δ		Part Wind Start	
	Hertz	Volts	Continuous Current	Locked Rotor Amps (Y)	Locked Rotor Amps (D)	Locked Rotor Amps (D)	Locked Rotor Amps (DD)
	60	460	302	305	915	646	950